



In-Wall Amplifier & Bluetooth Streaming Receiver

A0360

The A0360 In-Wall Amplifier & Bluetooth Streaming Receiver is designed to provide an all-in-one solution for TV audio amplification and music streaming. The A0360 features a built-in Bluetooth 4.2 module and allows audio switching between three sources. In addition, the A0360 features a “deep sleep” mode to conserve power and it packs a powerful 100 watt amplifier at 8 ohms or 200 watts at 4 ohms for a true enhanced system without a bulky power hungry AV Receiver. Set up and control from your IOS or Android phone enables a customized security code password, audio acoustic enhancements and personalized name setup.



KEY FEATURES

100 Watt integrated class D amplifier

CAT5 Multi-room Audio Input

Bluetooth 4.2 Module

Optical Tos-Link local Audio input

IR Control & IR Remote Code Learning

Power in front or 18 AWG wire in rear

Cascade to multiple Crescendo Amplifiers

SPECIFICATIONS*

IR Repeating: 30-60 kHz

IR Sensor Range: 40'

IR control via back CAT5, A0129 Keypad or Front

IR Receiver or IR-2501 remote head to 3.5mm input

decora style wall plate not included

Specifications subject to change

Operating Voltage: 24 VDC, 2.5 amp (included)

Speaker Impedance: 4-8 Ω

Output Power: 100W @ 8 Ω or 200W @ 4 Ω

Bluetooth 4.2 with Enhanced Audio Acoustics Flush Mount in 2-gang mud ring or standard 2-gang box

Security Code & Customize ID Name

Bypass Link button on front panel or IOS/Android App.

